

Analysis and Investigation of a Novel Microwave Sensor with High Q-Factor for Oil Sensing

By Tole Sutikno

1 Analysis and Investigation of a Novel Microwave Sensor with High Q-Factor for Oil Sensing

Ammar Alhegazi¹, Zahriladha Zakaria², Noor Azwan Shairi³, Tole Sutikno⁴, Rammah A. Alahnomi⁵,
Ahmed Ismail Abu-Khadrah⁶

^{1,2,3,5}Microwave Research Group (MRG), Centre for Telecommunication Research & Innovation (CeTRI),
Fakulti Kejuruteraan Elektronik dan Kejuruteraan Komputer (FKEKK), Universiti Teknikal Malaysia Melaka (UTeM),
4 Hang Tuah Jaya, 76100, Durian Tunggal, Melaka, Malaysia

⁴Department of Electrical Engineering, Universitas Ahmad Dahlan, Yogyakarta, Indonesia

⁶Computer Engineering Department, Faculty of Engineering, AMA International University Bahrain, 8041,
Salmabad, Kingdom of Bahrain

26 Article Info

Article history:

Received Oct 1, 2018

Revised Nov 24, 2018

Accepted Nov 30, 2018

Keywords:

Dielectric Properties
Gap Waveguide
Liquid Detection
Microwave Sensor
Oil Sensing

ABSTRACT

In this paper, a novel microwave sensor with high Q-factor for oil sensing is analyzed and investigated. The new design is based on a gap waveguide cavity resonator (GWCRC). To characterize and evaluate the sample, the oil under tested (OUT) is injected into a Teflon tube, which is passing through the microfluidic channel that is located in the middle of the cavity where the electric field concentrates. The results show that the proposed sensor has a high Q-factor of 4832. Moreover, the proposed design has the ability to sense and detect different types of oils with a small variation of permittivities such as Fish oil, Coconut oil, Olive oil, Linseed oil and Castor oil. The permittivity equation is extracted using the polynomial fitting method to define unknown dielectric properties of the OUT. The results show that the evaluated permittivity using the proposed sensor has a good agreement with the ideal permittivity. Therefore, the proposed sensor is a good candidate for oil processing in food industries.

Copyright © 2018 Institute of Advanced Engineering and Science.
All rights reserved.

Corresponding Author:

Zahriladha Zakaria,
Fakulti Kejuruteraan Elektronik dan Kejuruteraan Komputer (FKEKK),
Universiti Teknikal Malaysia Melaka (UTeM),
Hang Tuah Jaya, 76100, Durian Tunggal, Melaka, Malaysia.
Email: zahriladha@utem.edu.my

1. INTRODUCTION

Material sensing is very important for industries to control the quality and safety of the products. In food products, the concentration of some ingredients may influence the consumers and cause some diseases such as allergic, poison and sometimes it may cause cancer. Therefore, it is important to characterize the materials and identify the ingredients before selling the product to the consumers. Each material has a specific electric behaviour depends on the dielectric properties, thus material properties measurement plays an important role in increasing the demand number of industrial applications such as quality control in food industries and bio-sensing [1-2].

In the recent years, many methods of microwave sensor have been used for material properties measurement [3-4]. Different microwave sensors have been used in different applications such as planar split ring resonator for liquid [5] and solid [6-8] detection. Vertically stacked ring resonator has been used for Petroleum Oils sensing [9-10]. Another method by using a substrate integrated waveguide for liquid [11] and humidity [12] detection. These sensors attract research interest due to their advantages such as simplicity and low cost. However, these techniques showed low Q-factors, which may increase the error percentages and leads to inaccurate characterization of the material.

Microwave sensors depend on the frequency and quality factor of the resonator. Therefore, in this work the gap waveguide is chosen due to its high concentration of the electric field, which provides high Q-factor. Gap waveguide (GW) technique has gained research interest where it has been used for antenna design [13] and filter design [14]. However, for the first time, GW is used for material sensing in this article.

In this paper, a novel microwave sensor with high Q-factor for oil sensing is presented. The proposed sensor is designed based on gap waveguide cavity resonator (GWCR). The new geometry provides a high electric field in the cavity region, which leads to providing high Q-factor and high sensitivity. This technique is based on perturbation theory, where the oil under test (OUT) is placed in the maximum electric field region using a Teflon tube. The OUT complex permittivity is identified using the polynomial fitting method. Results from this study show that the evaluated permittivity using the proposed sensor has a good agreement with the ideal permittivity.

2. SENSOR DESIGN

The Q-factor is significant for microwave sensors. It shows how much the sensor is sensitive and accurate. It quantifies the amount of electric field concentration and the dissipated energy in the sensor. The loaded Q-factor (QL) can be calculated by using [15]:

$$\frac{1}{Q_L} = \frac{1}{Q_U} + \frac{1}{Q_E} \quad (1)$$

Where QU and QE are the unloaded and external quality factors respectively. QU is related to the loss of the sensor itself, and QE is related to the loss caused by the OUT which is calculated by using [16]:

$$Q_E = 10^{-[S_{21}(dB)/20]} Q_L \quad (2)$$

Therefore, the unloaded Q-factor can be calculated using [17]:

$$Q_U = \frac{Q_L}{1 - S_{21}} \quad (3)$$

Thus, to measure the Q-factor with the OUT, the following equation is used [18]:

$$Q_L = \frac{f_o}{BW} \quad (4)$$

Where f_o the resonant frequency and BW is the 3dB bandwidth. To calculate the Q-factor without the OUT, the following equation is used [19]:

$$Q_L = \frac{2f_o}{BW} \quad (5)$$

The optimum values of the proposed designed are obtained at 6.1 GHz as illustrated in Table 1. The proposed GWCR is constructed of upper and lower aluminium plates fed by two SMA connectors as shown in Figure 1. The lower plate consists of cavity, microfluidic channel and square array pins with size of 1 mm² and height less than $\lambda/4$. The upper metal plate consists of cavity and microfluidic channel, the SMA connectors are connected to the upper plate as well as shown in Figure 1. The upper plate is placed at 1 mm from the top of the pins surface. The two rows of array pins on each side of the ground plate provide a high electric field and increase the interaction with the OUT as shown in Figure 2. The interaction between the electric field and the OUT is linear, thus the change in relative permittivity of the OUT leads to change in the resonant frequency.

22

Table 1. The optimum values of the design parameters

Parameter	Value (mm)	Parameter	Value (mm)
W	38.20	d_2	18.00
L	35.40	x	5.10
d	1.00	s	1.60
d_1	1.50	p	1.80
y	6.35	t	5.00
h	15.75	h_1	21.70

30

The operation principle of the GWCR is based on the gap waveguide technology proposed in [20], where the upper plate acts as a perfect electric conductor, while the lower plate acts as a perfect magnetic conductor. Moreover, the square array pins in the lower plate restrict the propagation of the waves from all directions and this leads to increase the electric field in the pins area as shown in Figure 2. A Teflon tube with permittivity of 2.1 is inserted through the microfluidic channel to evaluate the OUT as shown in Figure 2.




Figure 1. Simulated structure of the proposed sensor using GWCR




Figure 2. Simulated electric field (v/m) of the proposed sensor at 6.1 GHz

3. RESULTS AND ANALYSIS

11

A parametric study is carried out for varied lengths of the pins as shown in Figure 3. It can be seen that the change in the length of the pins leads to change in the resonant frequency where the length of the pins increases, the resonant frequency decreases.

5

The proposed sensor shows its ability to sense and detect different types of oils such as Fish oil, Coconut oil, Olive oil, Linseed oil and stor oil, with relative permittivity of 2.6, 2.9, 3.1, 3.5, 4.7 respectively as shown in Figure 4. It can be observed that the relationship between the resonant frequency and the permittivity is inversely proportional to each other, where the resonant frequency is decreasing by increasing the permittivity, thus when the permittivity is 2.6 the resonant frequency appears at 6.0876 GHz, while when the permittivity is 4.7 the resonant appears at 6.0814 GHz.

10




Figure 3. Transmission coefficient of the proposed sensor for varied lengths of the pins

The polynomial graph of the proposed sensor is plotted according to the resonant frequency shifting and permittivity as shown in Figure 5. From the polynomial graph, the permittivity equation is extracted as follow:

$$\varepsilon' = 330.59f^2 - 4364.7f + 14322 \quad (6)$$




Figure 4. Transmission coefficient of the proposed sensor with and without OUT




Figure 5. Polynomial graph of the proposed sensor

To validate the accuracy of the proposed sensor, the permittivity of the OUT is evaluated using the proposed sensor and compared with the ideal permittivity, as shown in Table 2.

Table 2. Comparison between the evaluated permittivity by the proposed sensor and the ideal permittivity

OUT	Frequency (GHz)	Ideal Permittivity (ϵ')	Proposed sensor (ϵ')
Fish oil	6.0876	2.6	2.745
Coconut oil	6.0865	2.9	3.11
Olive oil	6.0858	3.1	3.357
Linseed oil	6.0848	3.5	3.699
Castor oil	6.0814	4.7	4.864

From Table 2 it can be said that a good agreement between the proposed sensor and the ideal permittivity, which means that the proposed sensor is accurate and has the ability to detect different types of oils. However, very small change of the permittivity between the proposed sensor and the ideal permittivity mainly due to the difference between the simulation environment and practical environment.

From the previous results, it can be said that the proposed sensor is reliable to be used for oil sensing in food industries. The results show that the proposed sensor has the highest Q-factor compared to the recently proposed sensors as shown in Table 3.

Table 3. Comparison between the proposed sensor and recently reported researches

Reference	Technique	Q _u -Factor
[5]	Planar double split ring resonator	525
[6]	Complementary split ring resonator	80
[7]	Planar symmetrical split ring resonator	652
[11]	Substrate Integrated waveguide	334.6
[10]	Vertically stacked ring resonator	146.67
[12]	Cavity Substrate Integrated Waveguides	≈300
[21]	Re-Entrant cavity	1190
[22]	Complementary folded arm split ring resonator	506
[23]	Multiple split ring resonator	430
Proposed sensor	Gap waveguide cavity resonator	4832

4. CONCLUSION

In this paper, a novel microwave sensor with high Q-factor for oil sensing is analyzed and investigated. This technique is based on gap waveguide cavity resonator (GWC). The results show that the GWC has the ability to detect different types of oils with a small variation of permittivities such as Fish oil, Coconut oil, Olive oil, Linseed oil and Castor oil. The GWC is designed and analyzed using CST Simulation Technology (CST). The electric field of the GWC is investigated, where the results show that the electric field more concentrates in the cavity, thus the OUT is placed in the cavity using Teflon tube. The results from this study show that the proposed sensor is a good candidate to be used for oil sensing in food industries.

ACKNOWLEDGEMENTS

This work was supported by UTeM Zamalah Scheme. The authors would also like to thank Centre for Research and Innovation Management (CRIM), Centre of Excellence, UTeM, UTeM's research grant JURNAL/2018/FKEKK/Q00001 and Universiti Teknikal Malaysia Melaka (UTeM) for their encouragement and help in sponsoring this study.

REFERENCES

- [1] S. N. Jha, K. Narsaiah, a. L. Basediya, R. Sharma, P. Jaiswal, R. Kumar, and R. Bhardwaj, "Measurement techniques and application of electrical properties for nondestructive quality evaluation of foods-a review," *J. Food Sci. Technol.*, vol. 48, no. 4, pp. 387–411, 2011.
- [2] N. A. Rahman, Z. Zakaria, R. A. Rahim, and D. Yosza, "Characterization : A review Planar Microwave Sensors for Accurate Measurement of Material Characterization : A Review," *TELKOMNIKA*, vol. 15, no. September, pp. 1108–1118, 2017.
- [3] A. Azuan, M. Bahar, Z. Zakaria, A. A. Isa, E. Ruslan, and R. A. Alahnomi, "A Review of Characterization Techniques for Materials ' Properties Measurement Using Microwave Resonant Sensor," *J. Telecommun. Electron. Comput. Eng.*, vol. 7, no. 2, pp. 1–6, 2015.
- [4] "Planar Microwave Sensors for Accurate Measurement of Material Characterization : A Review Refbacks," vol. 62, no. 274, p. 564604, 2017.
- [5] A. A. M. Bahar, Z. Zakaria, S. R. A. Rashid, A. A. M. Isa, R. A. Alahnomi, and D. Tunggal, "Dielectric analysis of liquid solvents using microwave resonator sensor for high efficiency measurement," *Microw. Opt. Technol. Lett.*, vol. 59, no. 2, pp. 367–371, 2017.
- [6] M. A. H. Ansari, A. K. Jha, and M. J. Akhtar, "Design and Application of the CSRR-Based Planar Sensor for Noninvasive Measurement of Complex Permittivity," *IEEE Sens. J.*, vol. 15, no. 12, pp. 7181–7189, 2015.
- [7] R. A. Alahnomi, Z. Zakaria, E. Ruslan, S. R. Ab Rashid, and A. A. Mohd Bahar, "High-Q sensor based on symmetrical split ring resonator with spurlines for solids material detection," *IEEE Sens. J.*, vol. 17, no. 9, pp. 2766–2775, 2017.
- [8] R. Alahnomi, N. Binti, A. Hamid, Z. Zakaria, T. Sutikno, and A. Azuan, "Microwave Planar Sensor for Permittivity Determination of Dielectric Materials," *Indones. J. Electr. Eng. Comput. Sci.*, vol. 11, no. 1, pp. 362–371, 2018.
- [9] A. A. Mohd Bahar, Z. Zakaria, A. A. Md Isa, Y. Dasril, and R. A. Alahnomi, "The CSIW Resonator Sensor for Microfluidic Characterization Using Defected Ground Structure," *J. Telecommun. Electron. Comput. Eng.*, vol. 10, no. 2–6, pp. 35–40, 2018.
- [10] S. Kulkarni and M. S. Joshi, "Design and Analysis of Shielded Vertically Stacked Ring Resonator as Complex Permittivity Sensor for Petroleum Oils," vol. 63, no. 8, pp. 2411–2417, 2015.
- [11] C. Liu and F. Tong, "An SIW Resonator Sensor for Liquid Permittivity Measurements at C Band," *IEEE Microw. Wirel. Components Lett.*, vol. 25, no. 11, pp. 751–753, 2015.
- [12] H. El Matbouly, N. Boubekeur, and F. Domingue, "Passive Microwave Substrate Integrated Cavity Resonator for Humidity Sensing," *IEEE Trans. Microw. Theory Tech.*, vol. 63, no. 12, pp. 4150–4156, 2015.
- [13] A. U. Zaman and P.-S. Kildal, "Slot antenna in ridge gap waveguide technology," *2012 6th Eur. Conf. Antennas Propag.*, no. March, pp. 3243–3244, 2012.
- [14] A. K. Horestani and M. Shahabadi, "Balanced Filter with Wideband Common-Mode Suppression in Groove Gap Waveguide Technology," *IEEE Microw. Wirel. Components Lett.*, vol. 28, no. 2, pp. 132–134, 2018.
- [15] E. Pucci, A. U. Zaman, E. Rajo-iglesias, P. Kildal, and A. Kishk, "Study of Q -factors of ridge and groove gap waveguide resonators," *IET Microwaves, Antennas Propag.*, vol. 7, no. May, pp. 900–908, 2013.
- [16] J. Papapolymerou, J. Cheng, J. East, and L. P. B. Katehi, "A Micromachined High- X-Band Resonator," *IEEE Microw. Guid. Wave Lett.*, vol. 7, no. 6, pp. 168–170, 1997.
- [17] Darko Kajfez, "Q-Factor," in *Encyclopedia of RF and Microwave Engineering*, K. Chang, Ed. Wiley Online Library, 2005.
- [18] David M. Pozar, "Microwave Engineering," book, *Univ. Massachusetts Amherst*, vol. 1, pp. 144–146, 2011.
- [19] A. Alhegazi, Z. Zakaria, R. A. Alahnomi, E. Ruslan, and S. R. A. Rashid, "Design of Double Ring Resonator (DRR) for Material Properties Measurement," in *IEEE International Conference on Intelligent & Advanced Systems*, 2016, pp. 1–6.
- [20] P. S. Kildal, E. Alfonso, A. Valero-Nogueira, and E. Rajo-Iglesias, "Local metamaterial-based waveguides in gaps between parallel metal plates," *IEEE Antennas Wirel. Propag. Lett.*, vol. 8, pp. 84–87, 2009.
- [21] H. Hamzah, A. Abduljabar, J. Lees, and A. Porch, "A Compact Microwave Microfluidic Sensor Using a Re-Entrant Cavity," *Sensors*, vol. 18, no. 3, p. 910, 2018.
- [22] N. A. Rahman, Z. Zakaria, R. A. Rahim, Y. Dasril, A. Azuan, and M. Bahar, "Dual Band Planar Microwave Sensor for Dielectric Characterization using Solid and Liquid Sample," *J. Telecommun. Electron. Comput. Eng.*, vol. 10, no. 2, pp. 27–32, 2018.
- [23] A. A. Mohd Bahar, Z. Zakaria, A. A. Md Isa, Y. Dasril, S. R. Ab Rashid, and R. a. Alahnomi, "The dielectric constant analysis for aqueous characterization using split ring resonator sensor," *J. Telecommun. Electron. Comput. Eng.*, vol. 9, no. 2–13, pp. 75–80, 2017.

Analysis and Investigation of a Novel Microwave Sensor with High Q-Factor for Oil Sensing

ORIGINALITY REPORT

24%

SIMILARITY INDEX

PRIMARY SOURCES

- 1

Rosario Peñaloza-Delgado, José Luis Olvera-Cervantes, María Elena Sosa-Morales, Tejinder Kaur Kataria, Alonso Corona-Chávez. "Dielectric characterization of vegetable oils during a heating cycle", Journal of Food Science and Technology, 2020
Crossref

48 words — 2%
- 2

M. A. Sazali, N. A. Shairi, Z. Zakaria. "Hybrid Microstrip Diplexer Design for Multi-band WiMAX Application in 2.3 and 3.5 GHz Bands", International Journal of Electrical and Computer Engineering (IJECE), 2018
Crossref

45 words — 2%
- 3

publications.lib.chalmers.se
Internet

36 words — 2%
- 4

Ammar Alhegazi, Zahriladha Zakaria, Noor Azwan Shairi, Tole Sutikno, Sharif Ahmed. "UWB Filtenna with Electronically Reconfigurable Band Notch using Defected Microstrip Structure", Indonesian Journal of Electrical Engineering and Computer Science, 2017
Crossref

35 words — 2%
- 5

www.freepatentsonline.com
Internet

27 words — 1%
- 6

www.ncbi.nlm.nih.gov

7

journals.plos.org

Internet

20 words — 1%

8

Alahnomi, Rammah A., Z. Zakaria, E. Ruslan, Amyrul Azuan Mohd Bahar., and S. R. Ab Rashid. "High sensitive microwave sensor based on symmetrical split ring resonator for material characterization", Microwave and Optical Technology Letters, 2016.

Crossref

18 words — 1%

9

Maryam Saadat-Safa, Vahid Nayyeri, Mostafa Khanjarian, Mohammad Soleimani, Omar M. Ramahi. "A CSRR-Based Sensor for Full Characterization of Magneto-Dielectric Materials", IEEE Transactions on Microwave Theory and Techniques, 2019

Crossref

18 words — 1%

10

www.journal.uad.ac.id

Internet

14 words — 1%

11

Guifeng Liu, Ying Liu, Shuxi Gong. "A coupled-fed loop antenna for metal-rimmed mobile phone applications", Microwave and Optical Technology Letters, 2017

Crossref

13 words — 1%

12

A. Alhegazi, Z. Zakaria, Rammah A. Alahnomi, E. Ruslan, S. R. Ab Rashid. "Design of double ring resonator (DRR) for material properties measurement", 2016 6th International Conference on Intelligent and Advanced Systems (ICIAS), 2016

Crossref

12 words — 1%

13

Aleksandr Ivanov, Timur Agliullin, Dario Laneve, Vincenza Portosi et al. "Design and Characterization

12 words — 1%

of a Microwave Planar Sensor for Dielectric Assessment of Vegetable Oils", Electronics, 2019

Crossref

- 14 Ali K. Horestani, Mahmoud Shahabadi. "Balanced Filter With Wideband Common-Mode Suppression in Groove Gap Waveguide Technology", IEEE Microwave and Wireless Components Letters, 2018 11 words — 1%

Crossref

- 15 Mohammad Arif Hussain Ansari, Abhishek Kumar Jha, Mohammad Jaleel Akhtar. "Design and Application of the CSRR-Based Planar Sensor for Noninvasive Measurement of Complex Permittivity", IEEE Sensors Journal, 2015 10 words — < 1%

Crossref

- 16 Mothana L. Attiah, A. A. M. Isa, Zahriladha Zakaria, Mowafak K. Mohsen, M. K. Abdulhameed, Ahmed M. Dinar. "Joint QoE-based user association and efficient cell-carrier distribution for enabling fully hybrid spectrum sharing approach in 5G mmWave cellular networks", Wireless Networks, 2019 10 words — < 1%

Crossref

- 17 tel.archives-ouvertes.fr 10 words — < 1%

Internet

- 18 Chorom Jang, Jin-Kwan Park, Hee-Jo Lee, Gi-Ho Yun, Jong-Gwan Yook. "Temperature-Corrected Fluidic Glucose Sensor Based on Microwave Resonator", Sensors, 2018 9 words — < 1%

Crossref

- 19 Muhammed Shafi K T, Abhishek Kumar Jha, M. Jaleel Akhtar. "Dual band RF sensor for testing of 9 words — < 1%

magnetic properties of materials using meandered line SRR",
Sensors and Actuators A: Physical, 2018

Crossref

20 Sandeep Kumar Singh, Nilesh Kumar Tiwari, Amit Kumar Yadav, M. Jaleel Akhtar, Kamal K. Kar. 9 words — < 1%

"Design of ZnO/N-Doped Graphene Nanohybrid Incorporated RF Complementary Split Ring Resonator Sensor for Ammonia Gas Detection", IEEE Sensors Journal, 2019

Crossref

21 eprints.whiterose.ac.uk 9 words — < 1%

Internet

22 www.ijarcsse.com 9 words — < 1%

Internet

23 Amyrul A. Mohd Bahar, Zahriladha Zakaria, Mohd K. Md Arshad, Rammah A. Alahnomi, Ahmed I. 8 words — < 1%

Abu - Khadrah, Weng Y. Sam. "Microfluidic biochemical sensor based on circular SIW - DMS approach for dielectric characterization application", International Journal of RF and Microwave Computer-Aided Engineering, 2019

Crossref

24 Antonio José Berenguer Verdú. "Analysis and design of efficient passive components for the millimeter-wave and THz bands", Universitat Politècnica de Valencia, 2017 8 words — < 1%

Crossref Posted Content

25 Fizza Ghulam Nabi, Kenneth Sundaraj, Chee Kiang Lam, Rajkumar Palaniappan. "Characterization and classification of asthmatic wheeze sounds according to severity level using spectral integrated features", Computers in Biology and Medicine, 2018 8 words — < 1%

Crossref

26 M.H. Jopri, A.R. Abdullah, M. Manap, M.R. Yusoff, T. Sutikno, M.F. Habban. "An Improved Detection and Classification Technique of Harmonic Signals in Power Distribution by Utilizing Spectrogram", International Journal of Electrical and Computer Engineering (IJECE), 2017

Crossref

8 words — < 1%

27 Qiulin Tan. "Chapter 23 Processing and Manufacturing Technology of Special Sensors", Springer Science and Business Media LLC, 2020

Crossref

8 words — < 1%

28 Sina Kiani, Pejman Rezaei, Moein Navaei, Mohammad Sadegh Abrishamian. "Microwave sensor for detection of solid material permittivity in single/multilayer samples with high quality factor", IEEE Sensors Journal, 2018

Crossref

8 words — < 1%

29 mdpi.com

Internet

8 words — < 1%

30 research.chalmers.se

Internet

8 words — < 1%

31 Zhihua Wei, Jie Huang, Jing Li, Guoqing Xu, Zongde Ju, Xuyang Liu, Xingsheng Ni. "A High-Sensitivity Microfluidic Sensor Based on a Substrate Integrated Waveguide Re-Entrant Cavity for Complex Permittivity Measurement of Liquids", Sensors, 2018

Crossref

7 words — < 1%

32 Rammah A. Alahnomi, Z. Zakaria, E. Ruslan, S. R. Ab Rashid, Amyrul Azuan Mohd Bahar, Azizah Shaaban. "Microwave bio-sensor based on symmetrical split ring resonator with spurline filters for therapeutic goods detection", PLOS ONE, 2017

6 words — < 1%

EXCLUDE QUOTES OFF
EXCLUDE BIBLIOGRAPHY ON

EXCLUDE MATCHES OFF